

WIRED NON-DIRECTIONAL PEOPLE COUNTING SYSTEM PC-QS06-D

DESCRIPTION:

A cost-effective solution, the SenSource PC-QS06-D is a basic, non-directional wired people counter. Each time its beam is broken, the wall mount LCD will increment by one until reset to zero. The system includes a sensor, LCD display and one reflector. The PC-QS06-D can be used as a stand-alone counter or upgraded for use with a Count Recorder data logger.

FEATURES:

- › Miniature sensor with articulating bracket and reflector for easy mounting and alignment
- › Modular system installs quickly with very little wiring
- › Small modular display mounts almost anywhere
- › Magnetic reset to prevent tampering
- › 7-year battery backup prevents data loss in case of power failure
- › Upgradeable for data collection with a Count Recorder



| PARAMETER | MIN | TYP | MAX | UNITS |
|--|--|-----|-----|-------|
| IR Sensor Range | 0.1 | - | 20 | Feet |
| IR Sensor Cable Length (6.5 ft supplied) | - | 6.5 | 500 | Feet |
| Supply Voltage (12V DC Power Adapter Included) | 9 | 12 | 15 | Volts |
| Supply Current | - | - | 50 | mA |
| Enclosure | Sensor: 1.38" x 0.59" x 1.38" / Display: 3.3"L x 3.3"W x 1.2"D | | | |

ORDERING:

- › People Counter with LCD Display, PC-QS06-D
- › People Counter with Count Recorder for data collection, PC-QS06-R*

OPTIONAL UPGRADES :

- Count Recorder for data collection, PCDL-1000 Requires Count Recorder Software & Download Cable, PCDC-USB1 (Required for use with PC-QS06-D)

